RECONFIGURABLE ANTENNAS

University of Maryland

APPROVED FOR PUBLIC RELEASE; DISTRIBUTION UNLIMITED.

19960311 205

Rome Laboratory
Air Force Materiel Command
Rome, New York

DTIC QUALITY INSPECTED 1

This report has been reviewed by the Rome Laboratory Public Affairs Office (PA) and is releasable to the National Technical Information Service (NTIS). At NTIS, it will be releasable to the general public, including foreign nations.

RL-TR-95- 274 has been reviewed and is approved for publication.

APPROVED:

RICHARD FEDORS
Project Engineer

FOR THE COMMANDER:

GARY D. BARMORE, Major, USAF
Deputy Director of Surveillance & Photonics

RECONFIGURABLE ANTENNAS

Ping-Tong Ho

Contractor: University of Maryland
Contract Number: F30602-94-C-0248
Effective Date of Contract:
Contract Expiration Date: **15 September 1994**
Short Title of Work: 15 March 1995

Period of Work Covered: Sep 94 - Mar 95

Principal Investigator: Ping-Tong Ho
             Phone: (301) 405-3740

RL Project Engineer: Richard Fedors
             Phone: (315) 330-3608

REPORT DOCUMENTATION PAGE

Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188), Washington, DC 20503.

1. AGENCY USE ONLY (Leave Blank)	2. REPORT DATE	3. REPORT TYPE AND DATES COVERED
	January 1996	Final Sep 94 - Mar 95

4. TITLE AND SUBTITLE	5. FUNDING NUMBERS
RECONFIGURABLE ANTENNAS	C - F30602-94-C-0248
	PE - 62702E
6. AUTHOR(S)	PR - A150
	TA - 00
Ping-Tong Ho	WU - 02

7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES)	8. PERFORMING ORGANIZATION REPORT NUMBER
University of Maryland Department of Electrical Engineering College Park MD 20742	N/A

9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)	10. SPONSORING/MONITORING AGENCY REPORT NUMBER
Advanced Research Projects Agency 3701 North Fairfax Drive Rome Laboratory/OCPC Arlington VA 22203-1714 26 Electronic Pky Rome NY 13441-4514	RL-TR-95-274

11. SUPPLEMENTARY NOTES

Rome Laboratory Project Engineer: Richard Fedors/OCPC/(315) 330-3608

12a. DISTRIBUTION/AVAILABILITY STATEMENT	12b. DISTRIBUTION CODE
Approved for public release; distribution unlimited.	

13. ABSTRACT (Maximum 200 words)

A radio frequency (RF) antenna was demonstrated by exciting charge carriers in a semiconductor. Using a common camera flash and a custom mask, portions of a four-inch diameter silicon wafer were illuminated to form a temporary electrically conductive pathway. The conductive path would momentarily mimic a thin-layer metallic antenna through which RF energy could be received or transmitted. Experiments in the 1-4 GHz range showed the optically-excited semiconductor antennas to be about 5 dB less efficient than similar dipole and bow-tie design metallic antennas. The silicon used had a carrier lifetime of approximately five microseconds when illuminated with an optical intensity of 10 watts per square centimeter. Changing illumination masks would allow the semiconductor antenna to be reconfigured to a variety of different antenna designs.

14. SUBJECT TERMS		15. NUMBER OF PAGES
		44
Antennas, Semiconductor, Linear dipole, Bow-tie, Radio frequency		16. PRICE CODE

17. SECURITY CLASSIFICATION OF REPORT	18. SECURITY CLASSIFICATION OF THIS PAGE	19. SECURITY CLASSIFICATION OF ABSTRACT	20. LIMITATION OF ABSTRACT
UNCLASSIFIED	UNCLASSIFIED	UNCLASSIFIED	UL

Table of Contents

Summary

A simple reconfigurable antenna was demonstrated using a common camera flash and stock 4"-diameter silicon wafers in the 1-4 GHz range. The reconfigurable antenna was triangular, and about 5 dB less efficient than a metallic antenna of the same design. Optical intensity of only about 10 W/cm^2 was required for the silicon used whose mobility and carrier lifetime were about 10^3 cm^2/V-s and 5 μs respectively.

Introduction

When a semiconductor is illuminated with light, the optical energy is absorbed, and free charge carriers are created which can conduct electrical current. If the illuminated pattern is designed to be an antenna pattern, then an antenna is created under illumination. Changing the illuminated pattern reconfigures the antenna. The goal of this contract was to demonstrate a simple reconfigurable antenna using an inexpensive, incoherent light source. The demonstration was successful: with a camera flash used in amateur photography and a 4"-diameter standard silicon wafer, a reconfigurable triangular ("bow-tie") antenna in the 1-3 GHz band was designed and constructed which radiated with an efficiency only 5 db less than a metallic antenna of the same structure. By reciprocity, the reconfigurable antenna will have the same efficiency when used as a receiving antenna. Furthermore, the camera flash had 10 times more energy than required, i.e., attenuating the flash output light 10 times did not change the antenna efficiency. This surplus of output light can be used in a liquid-crystal-display antenna mask controlled by a computer. A smaller reconfigurable antenna was constructed for and tested at 2-4 GHz to demonstrate a scaling law. This report presents the work done under the contract.

2

Experimental Set-up

The experimental set-up is illustrated in Figure 1. A camera flash illuminates a 4"-diameter silicon wafer through a mask whose opening forms the triangular antenna pattern. The illuminated pattern becomes the reconfigurable antenna which is connected to a microwave signal source via a strip line on the wafer. The receiving antenna is a metallic triangular on another 4"-diameter silicon wafer, of the same pattern as the reconfigurable antenna. The signal from the receiving antenna is connected to a spectrum analyzer. Most of the measurements were made with the camera flash 10 cm and the receiving antenna 8" from the reconfigurable antenna. The whole set-up was enclosed in a chamber lined with microwave absorbing materials. The set-up is shown in 2 perspectives in the attached photographs. Details of the components in the experiment are given below.

The Antennas

The triangular antennas were designed for a center frequency of 2 GHz or a wavelength of 15 cm. Following published data [J.D. Kraus, *Antennas*, 2nd Ed., McGraw-Hill 1988], the height of the triangle was made quarter wavelength and the full apex angle 60°, with the full antenna just fit within the 4" wafer diameter. Since the antennas were to be used free-standing with no ground plane on the back of the 0.25 mm-thick wafer, the vacuum wavelength had been used. On both the reconfigurable and the metallic antennas, a parallel strip metal transmission line was deposited to connect the center of the antenna in the middle of the silicon wafer to the OSM connector attached to the edge of the wafer. The antennas are illustrated in Figure 2. For experimental convenience, instead of straight triangular bases, circular arcs coincident with the wafer edge were used; no significant differences were expected. The impedance of a triangular

3

Figure 1   Experimental Set-up

Receiving antenna
Reconfigurable antenna
Camera flash

Receiving antenna
Reconfigurable antenna
Camera flash

Figure 2   Triangular Antennas

antenna is on the order of 100 Ω [Kraus, *op. cit.*], and it is balanced. The characteristic impedance of the rest of the system (source and detection) was 50 Ω and signals were transmitted with coaxial cables (unbalanced). For this contract whose duration was short and the measurements were mainly of a comparative rather than absolute nature (reconfigurable vs metallic), it was decided not to address these mismatches. To measure the effect of mismatches, the reflection from both the metallic and reconfigurable antennas when driven with a signal source was measured using a directional coupler. The results, shown in Figure 3, indicate that no more than half of the power was reflected despite the mismatches, and the antenna systems were usable for comparing the reconfigurable antenna to the metallic.

Metal deposition on silicon was by thermal evaporation of chromium (200 Å) followed by gold (2,000 A). The surface resistivity was on the order of 1 Ω square.

The silicon wafers used were 4" in diameter, 0.25 mm thick, undoped with a resistivity specified to be greater than 1 kΩ-cm. Characterization of the materials is reported below.

The Camera Flash

The camera flash, National PE-243, was typical of consumer flashes used in amateur photography. Its optical output energy was measured by an energy meter to be a few Joules. A fast detector displayed its waveform in time (Figure 4a) with a duration of about 250 μs. The output spread over approximately 90°. No analysis was made of its sprectral content; however, its spectrum would most likely be similar to the typical xenon flash spectrum shown in Figure 4b, with the characteristic blue tint. Spectral components with photon energies less than the silicon bandgap (1.1 eV) are not absorbed, while those in the UV are absorbed on the surface where charge carriers recombine much faster than in bulk. Thus only the spectral range from the

7

Figure 3   Reflection from Antennas

Figure 4 Flashlamp Characteristics

(a) Output Waveform
    Horizontal: 500 µs/div

(b) Typical spectrum

Figure 4.85 Spectral distribution
of intensity from an ILC 4L2
xenon flashlamp (51 mm long by
4 mm bore) operated in a critically
damped mode with 10 J
discharged in 115 µs. (Courtesy
of ILC.)

From "Building Scientific
Apparatus" by Moore,
Davis, and Coplan, 2/ed
Addison Wesley 1989

9

near infrared above the bandgap to the blue is effective in photoconduction.

Microwave Instrumentation

Two sweep/oscillators were used to cover the range 1 GHz - 4 GHz: HP 8620C with Plug-in 86222B (below 2.4 GHz), HP 8690B (2-4 GHz). Only one sweep/oscillator was used at one time, depending on the frequency at which measurements were made. The spectrum analyzer used was HP 8562A. For measurements of pulsed signals generated from the reconfigurable antenna, the spectrum analyzer was used in the single-frequency mode with a center frequency manually adjusted to the signal frequency. A microwave amplifier MiniCircuits ZHL4240 was used when needed.

Measurements and Results

The main measurement was on the efficiency of the reconfigurable antenna in the 1-3 GHz range relative to the metallic antenna. Supporting measurements were also made: antenna pattern, polarization, efficiency under different levels of illumination, and characteristics of the semiconductors used. A separate set of measurements were made on a reconfigurable antenna in the 2-4 GHz range to test a scaling law which states that the required optical illuminating power is proportional to the square of the radiating wavelength. These measurements and data are presented below.

Efficiency of the Reconfigurable Antenna

The efficiency of the reconfigurable antenna was measured using the set-up shown in Figure 1 in the following manner. The spectrum analyzer was set to single-frequency mode - it became in effect an oscilloscope with an narrow-band filter at the input whose center frequency was manually tuned to track the radiation frequency. A switch was used to trigger both the spectrum analyzer sweep (whose horizontal axis now represented time, not frequency) and, after a delay circuit, the camera flash. The signal source was fed to the reconfigurable antenna continuously; but the antenna radiated, and the spectrum analyzer detected a signal, only when the reconfigurable antenna was illuminated by the flash. A typical signal trace is shown in Figure 5 (the undershoot in the trace was pick-up). The signal level detected from the reconfigurable antenna was noted. The same measurement was repeated for different frequencies across the 1 - 3 GHz band. Next, the reconfigurable antenna was replaced by a metallic antenna of the same structure and the same measurements were made. The efficiency of the reconfigurable antenna relative to the metallic antenna is the ratio of the two sets of measurements, i.e.,

11

Figure 5
Typical Signal Detected on
Spectrum Analyzer in Single-
Frequency Mode
Total Horizontal Sweep: 50 ms

Relative efficiency of reconfigurable antenna

$$\frac{\text{power received by reconfigurable antenna}}{\text{power received by metallic antenna}}$$

The data are shown in Figure 6, from which the average efficiency of the reconfigurable antenna over the frequency range shown can be deduced to be about 5 dB less than the metallic antenna. At the distance between the flash and the reconfigurable antenna, the illumination was about 100 watts/cm^2. The 5 dB lower efficiency of the reconfigurable antenna was not due to insufficient optical power, as verified by the measurements presented next. The exact cause is not known, but it can be speculated to have come from the interconnection between the illuminated part and the metallic transmission line.

Efficiency vs. Illumination Intensity

To find the minimum optical intensity needed for the reconfigurable antenna, the flash output was attenuated at different levels and the efficiency measured. The set-up in Figure 1 was used, with the addition of neutral density filters in front of the flash lamp. The data, taken at 1.4 GHz, are shown in Figure 7. Almost no difference in efficiency was observed until the flash light was attenuated by ten-fold, implying that only about 10 W/cm^2 is needed.

Supporting Measurements on the Reconfigurable Antenna

Other measurements on the antenna were made to ensure that the reconfigurable antenna performed as expected.

(i) Pattern: The radiation from a triangular antenna is maximum in the direction perpendicular to the plane of the triangles, decreasing to zero on the plane. The receiving antenna was rotated around the axis through the apexes and parallel to the bases of the triangles (Figure 8). The

13

Figure 6 Efficiency of Reconfigurable Antenna

○ metallic antenna to metallic antenna
□ reconfigurable antenna to metallic antenna

Frequency in GHz

Received Power in dBm

Figure 7   Efficiency vs Illumination

Figure 8
Pattern Measurement Set-up

Figure 9 Antenna Pattern

Signal Strength in dB

Rotation Angle

pattern measured agrees with theory and is shown in Figure 9.

(ii) <u>Polarization</u>: The triangular antenna radiates and receives waves polarized along the antenna plane and perpendicular to the triangle bases. Rotating the receiving antenna 90° around the axis perpendicular to the plane through the apexes (Figure 10) should eliminate all signals. The experiment was carried out and this was indeed the case.

(iii) <u>Far/Near Field</u>: The two antennas in the experiment were placed 8" apart to maximize signals and minimize spurious reflections from surroundings. Proper antenna measurements should be made in the far field. In the near field, the radiation intensity is approximately independent of distance from the source. In the far field, the intensity decreases quadratically with distance. The transition from near to far field occurs at a distance $\sim D^2/\lambda$, where D is the dimension of the antenna, and λ the wavelength. Since the separation of the antennas was close to the approximate transition distance, signal-vs-distance measurements were made using two identical metallic triangular antennas, one as source and the other reception, along the corridor at night. The results, taken at 2 GHz, are shown in Fig. 11, where the separation of antennas in other measurements is marked. It can be seen that measurements had been made just in the far field.

Scaling Law

In a previous contract with the Air Force (No. F3060293C0184) a scaling law was proposed which states that the illuminating power needed for reconfigurable antenna designed for a certain wavelength increases with the square of the wavelength. For the triangular antenna, the width of the antenna is about 1/4 wavelength, therefore the area to be illuminated is proportional to the square of the wavelength and the total optical power illuminating the pattern also is proportional to the square of the

Figure 10
Polarization Check

19

Figure 11   Power vs Distance

Received Power in dBm

○ Experiment points
— linear fitting : y=3.4-20*log(x)

log(x), x is distance between the two antenna in cm

Figure 12   Comparison of two antennas

Received Power in dBm

Frequency in GHz

◯ large antenna
◇ small antenna

wavelength. To demonstrate this, a second reconfigurable antenna was constructed for a center frequency of 3 GHz by using a second mask with a width 2/3 that of the mask for the antenna at 2 GHz. The radiation from the smaller antenna was measured as before, and the results are shown in Figure 12 together with the data from the larger antenna. Since the optical *intensity* was the same in both cases, the *total optical power* intercepted by each antenna was proportional to the area of the antenna, or wavelength squared. At frequencies where both antennas operated, it is seen that both had similar performance, but with the smaller antenna requiring less optical power. Thus the scaling law was demonstrated.

Semiconductor Characterization

The important parameters of the silicon wafer for the reconfigurable antenna are mobility, carrier lifetime, and dark resistivity. The first two parameters determine the optical power needed, and the third should be high enough to make the wafer effectively insulating if not illuminated. The measure these parameters, the following experiments were carried out. The parallel strip lines on the reconfigurable antenna were used as electrodes, and the rest of the wafer was blocked from any light with a mask (Figure 13a). An area between the electrodes was used as a photoconductor, and biased with a DC voltage through a resistor in series (Figure 13b). The flash lamp illuminated the photoconductor, and the photo-resistance R was calculated from the measured voltage across the series resistance. If the carrier life-time τ is much shorter than the flash duration (verified later), then the mobility μ can be calculated from:

$$\mu = E_{photon} (w/L)/(\tau IR)$$

22

Leads
to
Electrodes

Mask

(a)
Photoconductor

light

photo-
conductor

DC bias

resistor

voltage
measured

(b)
Mobility measurement

Figure 13
Semiconductor Characterization

Figure 14   Photoresistance vs light intensity

Photoresistance in ohm

O large antenna
— linear fitting: R=1.06+3.35/T

1/T (T is transmittance of attenuators)

where E_{photon} is the photon energy, I the light intensity, w and L the gap width and length of the photoconductor respectively. With the flash lamp unattenuated, the photoresistance fell too low to be accurate, so measurement were made with different attenuators and the results are plotted in Figure 14. From these data, the mobility was estimated to be about 5×10^{-3} /τ(s) cm^2/V-s, with the carrier lifetime τ to be determined below. Extrapolating the photoresistance to infinite light intensity yields the contact resistance between the electrodes and the semiconductor, about 1 Ω. To determine the carrier lifetime, the flashlamp was replaced by a YAG laser which put out 15 ps at 1.06 μm, and the photo-conductance was observed with a fast oscilloscope to have lifetime of about 5 μs, which is interpreted as the carrier lifetime τ. With this additional information, the mobility was then estimated to be about 10^3 cm^2/V-s. The values of both the mobility and the carrier lifetime are very typical.

The dark resistivity was simply estimated from the dark resistance measured between the two electrodes to be about 10 kΩ-cm, well within the specification of the material and adequate for the experiments.

Discussion of Results and Recommendations for Further Work

The experiments performed demonstrated the practicality of the reconfigurable antenna illuminated with an inexpensive, incoherent optical source. The fact that even a common camera flash has ten times more energy than required points to further development of a computer-controlled reconfigurable antenna. The mask can be replaced by an inexpensive liquid-crystal-display panel, such as those used in portable television sets, whose transmission is controlled by a computer.

In a previous contract with the Air Force (No. F3060293C0184), an estimate was made of the required optical power to illuminate an antenna on silicon: 300 W at 1 GHz, with wavelength measured in silicon with mobility and carrier lifetime of 10^3 cm^2/V-s and 20 us respectively. Scaling the power by the parameters to those in the experiments verifies the estimate.

As already noted, the 5 dB difference in efficiency between the reconfigurable antenna and the metallic antenna was not due to insufficient illumination. Its cause may well come from the electrical contact between the illuminated part and the metallic part of the antenna. This should be looked into further.

It should be noted that all the components of an optically illuminated reconfigurable antenna are present in a small photo-copying machine: photoconductor (the drum is coated with selenium, for example), the lamp, the imaging system. With commercially available components, it should be able to design very inexpensive reconfigurable antenna systems.

26

DISTRIBUTION LIST

addresses	number of copies
RICHARD FEDORS ROME LABORATORY/OCPC 25 ELECTRONIC PKY ROME, NY 13441-4515	4
UNIVERSITY OF MARYLAND TECHNICAL REPORTS CENTER FOR: DR. PING-TONG HO ENGINEERING & PHYSICAL SCI. LIBRARY COLLEGE PARK, MD 20742	5
ROME LABORATORY/SUL TECHNICAL LIBRARY 26 ELECTRONIC PKY ROME NY 13441-4514	1
ATTENTION: DTIC-OCC DEFENSE TECHNICAL INFO CENTER 8725 JOHN J. KINGMAN ROAD, STE 0944 FT. BELVOIR, VA 22060-6218	2
ADVANCED RESEARCH PROJECTS AGENCY 3701 NORTH FAIRFAX DRIVE ARLINGTON VA 22203-1714	1
NAVAL WARFARE ASSESSMENT CENTER GIDEP (QA50) ATTN: RAYMOND TADROS PO BOX 8000 CORONA CA 91718-8000	1
WRIGHT LABORATORY/AAAI-2, BLDG 635 2185 AVIONICS CIRCLE WRIGHT-PATTERSON AFB OH 45433-7301	1
AFIT ACADEMIC LIBRARY/LDEE 2950 P STREET AREA B, BLDG 642 WRIGHT-PATTERSON AFB OH 45433-7765	1

```
WRIGHT LABORATORY/MLPO                          1
ATTN:  R. L. DENISON
BLDG 651
3005 P STREET, STE 6
WRIGHT-PATTERSON AFB OH 45433-7707

WRIGHT LABORATORY/MTE, BLDG 653                 1
2977 P STREET, STE 6
WRIGHT-PATTERSON AFB OH 45433-7739


AL/CFHI, BLDG 248                               1
ATTN:  GILBERT G. KUPERMAN
2255 H STREET
WRIGHT-PATTERSON AFB OH 45433-7022


AIR FORCE HUMAN RESOURCES LAB                    1
TECHNICAL DOCUMENTS CENTER
OL AL HSC/HRG, BLDG 190
WRIGHT-PATTERSON AFB OH 45433-7604


AUL/LSE                                         1
BLDG 1405
600 CHENNAULT CIRCLE
MAXWELL AFB AL 361126424


US ARMY SPACE & STRATEGIC                       1
DEFENSE COMMAND
CSSD-IM-PA
PO BOX 1500
HUNTSVILLE AL 35807-3801

NAVAL AIR WARFARE CENTER                        1
6000 E. 21ST STREET
INDIANAPOLIS IN 46219-2189


COMMANDING OFFICER                              1
NCCOSC RDTE DIVISION
ATTN: TECHNICAL LIBRARY,CODE 0274
53560 HULL STREET
SAN DIEGO CA 92152-5001

COMMANDER, TECHNICAL LIBRARY                    1
4747000/C0223
NAVAIRWARCENWPNDIV
1 ADMINISTRATION CIRCLE
CHINA LAKE CA 93555-6001
```

```
SPACE & NAVAL WARFARE SYSTEMS                         1
COMMAND, EXECUTIVE DIRECTOR (PD80A)
ATTN:  MR. CARL ANDRIANI
2451 CRYSTAL DRIVE
ARLINGTON VA 22245-5200


COMMANDER, SPACE & NAVAL WARFARE                      1
SYSTEMS COMMAND (CODE 32)
2451 CRYSTAL DRIVE
ARLINGTON VA 22245-5200



US ARMY MISSILE COMMAND                               2
AMSMI-RD-CS-R/DOCUMENTS
RSIC BLDG 4484
REDSTONE ARSENAL AL 35898-5241



ADVISORY GROUP ON ELECTRON DEVICES                   1
1745 JEFFERSON DAVIS HWY
SUITE 500
ARLINGTON VA 22202



LOS ALAMOS NATIONAL LABORATORY                       1
PO BOX 1663
REPORT LIBRARY, P364
LOS ALAMOS NM 87545



AEDC LIBRARY                                         1
TECHNICAL REPORTS FILE
100 KINDEL DRIVE, SUITE C211
ARNOLD AFB TN 37389-3211



COMMANDER                                            1
USAISC
ASHC-IMD-L, BLDG 61801
FT HUACHUCA AZ 85613-5000



US DEPT OF TRANSPORTATION LIBRARY                    1
FB10A, M-457, RM 930
800 INDEPENDENCE AVE, SW
WASH DC 22591



AFIWC/MSO                                            1
102 HALL BLVD, STE 315
SAN ANTONIO TX 78243-7016
```

```
DIRNSA                                              1
R509
9800 SAVAGE ROAD
FT MEADE MD 20755-6000


NSA/CSS                                             1
K1
FT MEADE MD 20755-6000


PHILLIPS LABORATORY                                 1
PL/TL (LIBRARY)
5 WRIGHT STREET
HANSCOM AFB MA 01731-3004


THE MITRE CORPORATION                               1
ATTN: E. LADURE
D460
202 BURLINGTON RD
BEDFORD MA 01732


OUSD(P)/DTSA/DUTD                                   2
ATTN:  PATRICK G. SULLIVAN, JR.
400 ARMY NAVY DRIVE
SUITE 300
ARLINGTON VA 22202


NY PHOTONIC DEVELOPMENT CORP                        1
MVCC ROME CAMPUS
UPPER FLOYD AVE
ROME, NY   13440


ROME LABORATORY/C3BC                                1
ATTN: ROBERT KAMINSKI
525 BROOKS RD
ROME, NY 13441-4515


DEPARTMENT  OF DEFENSE                              1
ATTN:  R222
9800 SAVAGE ROAD
FORT MEADE, MD 20755-6000


ROME LABORATORY/ERAA                                1
ATTN:  DAVID D. CURTIS
HANSCOM AFB, MA 01731-2909
```

```
ROME LABORATORY/ERAC                                  1
ATTN:   J. BRUCE THAXTER
HANSCOM AFB, MA 01731-2909


ROME LABORATORY/ERO                                   1
ATTN:   RICHARD PAYNE
HANSCOM AFB, MA 01731-2909


ROME LABORATORY/EROC                                  1
ATTN:   JOSEPH P. LORENZO
HANSCOM AFB, MA 017331-2909


ROME LABORATORY/EROP                                  1
ATTN:   JOSEPH L. HORNER
HANSCOM AFB, MA 01731-2909


ROME LABORATORY/EROC                                  1
ATTN:   RICHARD A. SOREF
HANSCOM AFB, MA 01731-2909


ROME LABORATORY/ERXE                                  1
ATTN:   JOHN J. LARKIN
HANSCOM AFB, MA 01731-2908


ROME LABORATORY/ERDR                                  1
ATTN:   GEORGE RAMSEYER
525 BROOKS RD
ROME, NY 13441-4505


ROME LABORATORY/IRAP                                  1
ATTN:   ALBERT A. JAMBERDINO
32 HANGAR RD
ROME, NY 13441-4114


ROME LABORATORY/OC                                    1
ATTN:   BRIAN M. HENDRICKSON
25 ELECTRONIC PKY
ROME, NY 13441-4515
```

```
ROME LABORATORY/OCPC                              1
ATTN:  GREGORY J. ZAGAR
25 ELECTRONIC PKY
ROME, NY 13441-4515


ROME LABORATORY/OCPA                              1
ATTN:  ANDREW R. PIRICH
25 ELECTRONIC PKY
ROME, NY 13441-4515


ROME LABORATORY/OCPB                              1
ATTN:  RICHARD J. MICHALAK
25 ELECTRONIC PKY
ROME, NY 13441-4515


ROME LABORATORY/OCTS                              1
ATTN: RICHARD LINDERMAN
26 ELECTRONIC PKY
ROME, NY 13441-4514


ADVANCED RESEARCH PROJECTS AGENCY                 1
ATTN:  BERTRAM HUI
3701 NORTH FAIRFAX DRIVE
ARLINGTON, VA 22203-1714


ROME LABORATORY/OCPC                              4
ATTN:  NORM BERNSTEIN
25 ELECTRONIC PKY
ROME, NY 13441-4515
```

MISSION

OF

ROME LABORATORY

Mission. The mission of Rome Laboratory is to advance the science and technologies of command, control, communications and intelligence and to transition them into systems to meet customer needs. To achieve this, Rome Lab:

    a. Conducts vigorous research, development and test programs in all applicable technologies;

    b. Transitions technology to current and future systems to improve operational capability, readiness, and supportability;

    c. Provides a full range of technical support to Air Force Materiel Command product centers and other Air Force organizations;

    d. Promotes transfer of technology to the private sector;

    e. Maintains leading edge technological expertise in the areas of surveillance, communications, command and control, intelligence, reliability science, electro-magnetic technology, photonics, signal processing, and computational science.

The thrust areas of technical competence include: Surveillance, Communications, Command and Control, Intelligence, Signal Processing, Computer Science and Technology, Electromagnetic Technology, Photonics and Reliability Sciences.